

System Recovery

1. Environment requirement
 - MicroSD card (8GB capacity is recommend) and a SD card adapter.
2. Create a bootable SD for Windows
 - 2.1 Download 'win32diskimager' from <https://sourceforge.net/projects/win32diskimager/>
 - 2.2 Download HC-31xx image (filename: hc3xx0_installer_2018xxxx.img) from <http://www.artila.com/download/AM335X/Linux/image/>
 - 2.3 Run 'win32diskimager' and select image file then press 'Write' button



3. Insert bootable SD to HC3120 and short JP9 then Power On
4. Select image from Screen to installation



5. After install is finished, open JP9 then Reboot